

ANZ



IQ7A Microinverter

The high-powered smart grid-ready IQ7A Microinverter dramatically simplifies the installation process while achieving the highest system efficiency for systems with 60-cell, 66-cell, and 72-cell PV modules.

Part of the Enphase IQ System, the IQ7A Microinverter integrates with the IQ Gateway Metered, IQ Battery, and the Enphase App monitoring and analysis software.

The IQ Series Microinverters extend the reliability standards set forth by previous generations and undergo over a million hours of power-on testing, enabling Enphase to provide an industry-leading warranty.



IQ Gateway Part of the Enphase Energy System, IQ7 Series Microinverters integrate with the IQ Battery, IQ Gateway, and the Enphase App monitoring and analysis software.



Q-DCC-2 adapter cable Connect PV modules quickly and easily to IQ7 Series Microinverters using the included Q-DCC-2 adapter cable with plug-and-play MC4 connectors.



IQ Cabling Install microinverters quickly and safely with IQ Cabling. With multi-phase

with IQ Cabling. With multi-phase IQ Cabling, the installed capacity is automatically distributed evenly across all three phases.



IQ7 Series Microinverters redefine reliability standards with more than one million cumulative hours of power-on testing, enabling an industry-leading limited warranty of up to 10 years.

High power

• Peak output power is 366 VA

Easy to install

- · Lightweight and simple
- Faster installation with improved, lighter two-wire cabling
- Built-in rapid shutdown compliant

Efficient and reliable

- Optimized for high-powered 60-cell, 66-cell, and 72-cell PV modules
- Highest EU efficiency of 96.5%
- · More than a million hours of testing
- Class II double-insulated IP67
 enclosure

Smart grid-ready

- Complies with advanced grid support, voltage, and frequency ride-through requirements
- IQ Gateway and internet connection are required
- · Configurable for varying grid profiles

© 2023 Enphase Energy. All rights reserved. Enphase, the e and CC logos, IQ, and certain other marks listed at <u>https://enphase.com/trademark-usage-guidelines</u> are trademarks of Enphase Energy, Inc. in the US and other countries. Data subject to change.

IQ7A Microinverter

INPUT (DC)	IQ7A-72-2-INT	
Commonly used module pairings ¹	295 W-460 W	
Module compatibility	60-cell, 66-cell, and 72-cell PV modules	
Maximum input DC voltage	58 V	
PV input operating voltage range ²	18 V-58 V	
Minimum/Maximum start voltage	33 V/58 V	
Max DC short circuit current (module lsc) ³	15 A	
Overvoltage class DC port	Ш	
DC port backfeed current	ΟΑ	
OUTPUT (AC)		
Peak output power	366 VA	
Maximum continuous output power	349 VA	
Nominal (L-N) voltage/range ⁴	230 V/219-264 V	
Maximum continuous output current	1.52 A	
Nominal frequency	50 Hz	
Extended frequency range	45-55 Hz	
AC short circuit fault current over three cycles	5.8 Arms	
Maximum units per 20 A (L-N) branch circuit ⁵	11 (single-phase)	
Overvoltage class AC port	ш	
AC port backfeed current	18 mA	
Power factor setting	1.0	
Power factor (adjustable)	0.8 leading0.8 lagging	
EN 50530 (EU) weighted efficiency	96.5%	
MECHANICAL		
Ambient temperature range	-40°C to 60°C	
Relative humidity range	4% to 100% (condensing)	
Maximum altitude	2,000 m	
DC connector type	Bulkhead with MC4 locking type connector	
Dimensions (HxWxD)	212 mm x 175 mm x 30.2 mm (without bracket)	
Weight	1.08 kg (2.38 lbs)	
Cooling	Natural convection—No fans	
Approved for wet locations	Yes	
Pollution degree	PD3	
Enclosure	Class II double-insulated, corrosion-resistant polymeric enclosure	
Environmental category/UV exposure rating	Outdoor - IP67	
FEATURES		
Communication	Power line communication (PLC)	
Monitoring	Enphase Installer Portal and Enphase App monitoring options Compatible with IQ Gateway Metered	
Compliance	AS/NZS 4777.2, RCM, IEC/EN 61000-6-3, IEC/EN 62109-1, IEC/EN 62109-2, EN 50549, G98/G99, VDE-AR-N-4105	

 $1. No enforced DC/AC ratio. See the compatibility calculator at {{\tt https://enphase.com/en-au/support/module-compatibility}. Comparison of the compatibility of the compatibili$

No enforced DC/AC ratio. See the compatibility calculator at <u>https://enpnase.com/en-au/support/module</u>
 EU peak power tracking voltage range is 38 V to 43 V.
 Maximum continuous input DC current is 10.2 A.
 Voltage range can be extended beyond nominal if required by the utility.
 Limits may vary. Refer to local requirements to define the number of microinverters per branch in your area.

Revision history

REVISON	DATE	DESCRIPTION
DSH-00003-1.0	May 2023	Initial release